



Amplitude Modulated 40 KHz CaveTransceiver and RDF  
Peter Robertson VSA

1998

	On and Receiver receiving 800Hz tone TX- RED RX- GREEN	Parts as DJS built 2007							
<b>Note 7</b>	Mercury tilt switches can be used in waterproof cases to eliminate extra holes in cabinet	DICK SMITH	P7860						
<b>Note 8</b>	Loop consists of 14 Turns of wire. approx 20 Mtrs of wire								
	To wind use as a former a piece of wood about 20 mm thick and 70cm long.								
	Wind the 14 turns from end to end then slide the coil off and form a loop.								
	Tape or use cable ties to hold it in a loop								
	Solder the loop to one end of the coax and fit the BNC plug on the other.								
	Fine tune the loop as necessary then seal bare connections to waterproof.								
<b>Note 9</b>	Cabinet has two end caps, seal one end up with silicone sealant to waterproof.								
	Fit all external controls, Speaker, Power cable Gland Etc to other end. Install PCB Guides inside cabinet only after all parts have been fitted								
	*****								
	Please Note The parts listed as Dick Smith are given only as a reference to identify in their Catalogue. They can be purchased at many other outlets and Trade Houses.								
	*****								